

## UHF - USB Desktop Reader / Writer (RF Power can be adjusted)

### Model No. WRD-130U-X1 (Built-in antenna)

**Frequency:** 860~928 MHz (Set frequency on demand)

US 902-928, TW 922-928, CN 920-925, CN2 840-845, EU 865-868, JP 916-921,  
KR 917-921, VN 918-923, EU2 916-920, IN 865-867

**Protocols :** EPC C1G2 ISO 18000-6C

**Interface :** USB - Keyboard emulator / HID/USB CDC (Visual Serial Port)

Option for RS232 / UART in TTL level / I2C

**Supply voltage :** USB Port (3 - 7 VDC)

**RF Power Output :** -2dBm ~18 dBm

**Operation range :** 1 ~ 80 cm (depend on tag)

Operation Temp. 0°C to +50°C (+32°F to +122°F)

**Dimension :** 448 x 225 x 26 mm

### Description :

With the function as USB Interface, Desktop Reader

WRD-130U-X1 series is a read / write

function, which is applicable for

— **Library management / Point of Sales / Registration /  
Factory production line.**



The specification is preliminary and subject to change without notice.

WC15P01 V1.0

**Wingsafe Technology Inc.**

TEL:(886)-2-2945-8966 FAX:(886)-2-294-8086

More Information, Please contact [wingsafe@gmail.com](mailto:wingsafe@gmail.com)